

Basic Sign Operation

- Plug in the sign to the power supply.
- Turn the sign ON or OFF – Press Alt + Run

Creating Messages

The sign has a memory hot key that displays the message programmed.

To Program message:

1. Press > PROG
2. Using Remote control ,Type > 01
3. Press > Enter
4. Use PREV or NEXT to change animation
5. Press > Right arrow key to find start point (after animation point)
Example [FLASH] **I**his is the point to begin.
6. Continue to add your message using CAP (Capitals), SPA (Space), DEL (Delete)
7. Press > RUN
8. Save Y/N

Animations

To make or change animations, at the point where you would like an animation,

1. Press ALT – ENTER at the **S**tart point of animation.
2. Use PREV or NEXT buttons to change animation style.
3. At the end of desired animation length. Press ALT ENTER choose other animation.
e.g. [IMMED] **I**his opens immediately [SCROLL] **I**his scroll in from the side [FLASH] **F**lashing
Word [SCROLL] **I**he words scroll in again.
4. Press > Alt-SPE for [SPEED]

Sequences

1. You can run a sequence of messages e.g. 01, followed by 02, followed by 06, 07 etc.
2. To begin a sequence, first you must create two or more Messages (01,02 etc)
3. Press PROG
4. Type S1
5. Type 01 02 06 (as you require).
6. Press RUN
7. Save Y/N